

Manual telefone OpenStage 10T

Para maiores informações sobre este ou outro produto Siemens ligue:

Tel : 11 2858-0544 ou acesse :

www.asservice.com.br

Documentation

HiPath 500, HiPath 3000

OpenStage 10 T

User Guide



Communication for the open minded

SIEMENS

Siemens Enterprise Communications
www.siemens-enterprise.com

Important information



Never open the telephone or a key module. Should you encounter any problems, contact your service personnel.



Use only original Siemens accessories. The use of other accessories may be hazardous and will render the warranty and the CE marking invalid.

Trademarks



The device conforms to the EU directive 1999/5/EC as attested by the CE marking.



All electrical and electronic products should be disposed of separately from the municipal waste stream via designated collection facilities appointed by the government or the local authorities.

Proper disposal and separate collection of your old appliance will help prevent potential damage to the environment and human health. It is a prerequisite for reuse and recycling of used electrical and electronic equipment.

For more detailed information about disposal of your old appliance, please contact your city office, waste disposal service, the shop where you purchased the product or your sales representative.

The statements quoted above are only fully valid for equipment which is installed and sold in the countries of the European Union and is covered by the directive 2002/96/EC. Countries outside the European Union may impose other regulations regarding the disposal of electrical and electronic equipment.

Location of the telephone

- The telephone should be operated in a controlled environment with an ambient temperature between 5°C and 40°C.
- Do not install the telephone in a room where large quantities of dust accumulate; this can considerably reduce the service life of the telephone.
- Do not expose the telephone to direct sunlight or any other source of heat, as this is liable to damage the electronic components and the plastic casing.
- Do not operate the telephone in damp environments such as bathrooms.

Product support on the Internet

Information and support for our products can be found on the Internet:
<http://www.siemens-enterprise.com/>.

Technical notes, current information about firmware updates, frequently asked questions and lots more can be found on the Internet at:
<http://wiki.siemens-enterprise.com/>.

Contents

Important information2

Trademarks	2
Location of the telephone	3
Product support on the Internet	3

General information.....8

About this manual	8
Service.....	8
Intended use	9
Telephone type	9
Team functions	9

Getting to know your OpenStage phone10

The user interface of your OpenStage 10 T	10
Keys.....	11
Audio keys.....	11
Function keys.....	11
Mailbox	12
Messages	12
Voicemail	12
Calling functions	13
Using codes.....	13
Using function keys	14

Basic functions.....15

Answering calls	15
Answering a call via the handset	15
Open listening in the room during a call	16
Making calls.....	17
Dial.....	17
On-hook dialing	17
Dialing with DDS keys	18
Redialing a number	18
Ending a call.....	18
Rejecting calls	19
Turning the microphone on and off	19
Calling a second party (consultation)	20
Switching to the held party (alternating)	20
Transferring a call.....	21

Call forwarding	22
Using variable call forwarding	22
Forwarding key	23
Using call forwarding no reply (CFNR)	24
Call forwarding in the carrier network and forwarding multiple subscriber numbers (MSN) (not for U.S.)	25
Using callback	26
Storing a callback	26
Accepting a callback	26
Deleting saved callbacks (all)	26

Enhanced phone functions 27

Answering calls	27
Accepting a specific call for your colleague	27
Using the speakerphone	27
Answering calls from the entrance telephone and opening the door	28
Accepting a call from an answering machine	29
Making calls	30
Making calls using system speed-dial numbers	30
Dialing with speed-dial keys	30
Talking to your colleague with a speaker call	31
Talking to your colleague with discreet calling (not for HiPath 500)	32
Automatic connection setup (hotline)	32
Assigning a station number (not for U.S.)	32
Associated dialing/dialing aid	33
During a call	34
Using call waiting (second call)	34
Preventing and allowing call waiting (automatic camp-on)	35
Turning the call waiting tone on and off	35
Accepting call on hold	35
Parking a call	36
Conducting a conference	37
Activating tone dialing/DTMF suffix-dialing	38
Recording calls	39
Transferring a call after a speaker call announcement in a group	40
Send trunk flash (not for HiPath 500)	40
If you cannot reach a destination	41
Call waiting (camp-on)	41
Busy override – joining a call in progress	41
Using night answer	42

Displaying and assigning call charges 43

Dialing with call charge assignment	43
---	----

Privacy/security	44
Activating/deactivating "Do not disturb"	44
Caller ID suppression	45
Silent Monitor (not for HiPath 500)	45
Monitoring a room	46
Trace call: identifying anonymous callers (not for U.S.)	47
Locking the telephone to prevent unauthorized use	47
Locking another telephone to prevent unauthorized use	48
Saving your PIN	49
More functions/services	50
Appointments function	50
Saving appointments	50
Using timed reminders	50
Sending a message	51
Creating and sending a message	51
Editing incoming messages	52
Using another telephone like your own for a call	52
Changing a number (after exchanging/moving/relocating a phone)	53
Fax details and message on answering machine	53
Resetting services and functions (system-wide cancellation for a telephone)	54
Activating functions for another telephone	55
Using system functions from outside	
DISA (direct inward system access)	56
Controlling Connected Computers or Their Programs/Tel. Data Service	58
Communicating with PC applications over a CSTA interface	59
Controlling relays (only for HiPath 3000)	60
Paging persons (not for U.S., not for HiPath 500)	61
Using team functions	62
Activating/deactivating a group call	62
Accepting a call for another member of your team	63
Ringling group	63
Uniform Call Distribution (UCD)	64
Individual phone configuration	66
Adjusting audio settings	66
Adjusting the receiving volume during a call	66
Adjusting the ring volume	66
Adjusting the ring tone	66

Testing the phone67
Phone functions, testing 67

Fixing problems68
Contact partner in the case of problems 68
Troubleshooting 68
Caring for your telephone 68

Index69

Overview of functions and codes73

General information

About this manual


This document contains general descriptions of the technical options, which may not always be available in individual cases. The respective features must therefore be individually defined in the terms of the contract.

If a particular function on your phone is not available to you, this may be due to one of the following reasons:

- The function is not configured for you or your telephone. Please contact your system support representative.
- Your communications platform does not feature this function. Please contact your Siemens sales partner for information on how to upgrade.

This user guide is intended to help you familiarize yourself with OpenStage and all of its functions. It contains important information on the safe and proper operation of your OpenStage phone. These instructions should be strictly complied with to avoid operating errors and ensure optimum use of your multifunctional telephone in the network.


These instructions should be read and followed by every person installing, operating or programming an OpenStage phone.

 For your own protection, please read the section dealing with safety in detail. Follow the safety instructions carefully in order to avoid endangering yourself or other persons and to prevent damage to the unit.

This user guide is designed to be simple and easy to understand, providing clear step-by-step instructions for operating your OpenStage phone.

Administrative tasks are dealt with in a separate manual. The Quick Reference Guide contains quick and reliable explanations of frequently used functions.

Service

 The Siemens service department can only help you if you experience problems or defects with the phone. Should you have any questions regarding operation, your specialist retailer or network administrator will gladly help you. For queries regarding connection of the telephone, please contact your network provider.

If you experience problems or defects with the phone, please dial the service number for your country.

Intended use

The OpenStage phone was developed as a device for speech transmission and should be placed on the desk or mounted on the wall. Any other use is regarded as unauthorized.

Telephone type

The identification details (exact product designation and serial number) of your telephone can be found on the nameplate on the underside of the base unit. Specific details concerning your communications platform can be obtained from your service technician.

Please have this information ready when you contact our service department regarding faults or problems with the product.

Team functions

To increase the efficiency of telephony, your service personnel can configure various Team functions such as pickup groups, hunt groups, and call distribution groups.

Getting to know your OpenStage phone

The following sections describe the most frequently used operating elements on your OpenStage phone.

The user interface of your OpenStage 10 T



1	You can make and receive calls as normal using the handset .
2	Loudspeaker for open listening.
3	The function keys can be programmed with station numbers and functions by your service personnel → page 11.
4	Audio keys are also available, allowing you to optimally configure the audio features on your telephone → page 11.
5	The keypad is provided for input of phone numbers/codes.

Properties of your OpenStage 10 T

Wall mounting	✓
---------------	---

Keys


Audio keys



Key	Function when key is pressed
	Set the volume lower → page 66.
	Turn speaker on/off (with red LED key) → page 16.
	Set the volume higher → page 66.

Function keys

Your OpenStage 10 T features three function keys that can be programmed with functions or station numbers by your service personnel.



Depending on how they are programmed, you can use the keys as:

- function keys
- redial keys
- trunk keys




You can program all programmable keys (except "Shift") on two levels. The "Shift" key must be configured for this, and extended key functionality must be active (contact your service personnel).

In addition to functions and procedures, external phone numbers and internal numbers can also be saved without LED display on the second level.

Your service personnel can customize the default assignment in line with your needs and requirements once the order has been placed.

The status of a function is shown by the LED on the corresponding function key.

Meaning of LED displays on function keys and DSS keys

LED		Meaning of function key	Meaning of DSS key
	Off	The function is deactivated.	The line is free.
	Flashing ^[1]	The function is in use.	The line is busy.
	On	The function is activated.	There is a call on the line.

[1] In this manual, flashing keys are identified by this icon, regardless of the flashing interval. The flashing interval represents different statuses, which are described in detail in the corresponding sections of the manual.

Mailbox

Depending on your communication platform and its configuration (contact your service personnel), you can use the mailbox key to access incoming messages and messages from services such as HiPath Xpressions.

Messages

In idle mode, the following signals alert you to the presence of a new message:

- The LED on the "Mailbox" key lights up.
- A special tone (continuous buzzing) or an announcement is audible when you lift the handset.



For a description of how to edit the entries → page 52.

Voicemail

If your telephone is connected to a voicemail system (such as Entry Voice Mail), the Mailbox key will also light up to alert you to any messages that have arrived.

To play back your voicemail, follow the instructions.


Step by Step

Calling functions

Your communication system dynamically customizes its extensive range of functions depending on the given situation. You can activate the functions available on your OpenStage 10 T via the individually programmed function keys and/or with an appropriate code.

Using codes

All communication system functions can be activated via codes.

 Codes that activate functions are always preceded by the star key, whereas codes that deactivate/delete functions always start with the pound key.

Making settings in idle mode

Example:

Your phone is in idle mode.



Enter the code to activate the "Do not disturb" feature.



The speaker key lights up when you start programming and goes out when the operation is over.



In some situations, an acoustic signal is also output.

Activating functions during a call

Example:



You are conducting a consultation call and would like to toggle between the two parties.




Press the "Consult" key.



Enter the code.

An overview of the most important procedures and default codes is provided in the appendix to this user guide → page 73.

Default codes are also specified in the descriptions in the main part of this user guide.

 Default codes can be modified by your service personnel.

Step by Step

Using function keys

Your service personnel can program the three function keys with frequently used functions. You can activate a function by simply pressing the relevant key (if permitted by the current situation).

For more information, see → page 11.


Example:

Your phone is in idle mode.

- Press the "DoNotDisturb" key. The LED lights up. Do not disturb is active.

Step by Step


Basic functions

 Please read the introductory chapter "Getting to know your OpenStage phone" → page 10 carefully before performing any of the steps described here on your phone.

Answering calls

Your OpenStage phone rings with the tone signal set when an incoming call is received.



- When you receive an internal call, your telephone rings once every four seconds (single-tone sequence).
- When you receive an external call, your telephone rings twice in rapid succession every four seconds (dual-tone sequence).
- When you receive a call from the entrance telephone, your telephone rings three times in rapid succession every four seconds (triple-tone sequence).
- If a call is waiting, you hear a short tone (beep) every six seconds.

 Your service personnel can adjust the ring cadence for external and internal calls for you. In other words, different ring cadences can be set for different internal callers.

Answering a call via the handset

The phone is ringing.

Lift the handset.

if nec.  or 

Set the call volume. Keep pressing the key until the desired volume is set.

Step by Step

Open listening in the room during a call

You can let other people in the room join in on the call. Let the other party know that you have turned on the speaker.

Prerequisite: You are conducting a call via the handset.

Activating



Press the speaker key. The LED lights up.

Deactivating



Press the speaker key. The LED goes out.

Step by Step

Making calls

Dial



Lift the handset.



Internal calls: Enter the station number.
External calls: Enter the external code and the station number.

The called party does not answer or is busy



Replace the handset.

or



if available:
Press the "Release" key.

On-hook dialing



Internal calls: Enter the station number.
External calls: Enter the external code and the station number.



Your system may also be programmed so that you have to press the "internal" key before you dial an internal number.

To call an external party, you have to enter an external code before dialing the party's telephone number (Prime Line is not active; contact your service personnel).

The other party answers with speaker



Lift the handset.

The called party does not answer or is busy:



Press the speaker key. The LED goes out.

or





if available:
Press the "Release" key.

Step by Step

Dialing with DDS keys


Prerequisite: Redial keys are programmed on your phone.

 Press the key with a saved number.
If the number is saved on the second layer, press the shift key first.

 You can press the DDS key during a call and automatically initiate a callback → page 20.


Redialing a number

The last external station number dialed is automatically saved.


 If this feature is configured (contact your service personnel), account codes entered are also saved → page 43.

You can redial them simply by pressing a key.


Prerequisite: The "Redial" key is programmed on your telephone.

 Lift the handset.

 Press the "Redial" key

 On a multi-line phone, the last number dialed on the primary line is always saved.

Ending a call

 Replace the handset.

or if available:

 Press the "Release" key.


Step by Step

Rejecting calls

You can reject calls which you do not wish to take. The call is then signaled at another definable telephone (contact your service personnel).

The phone is ringing.

if available:

 Press the "Release" key.

If a call cannot be rejected, your telephone will continue to ring.


Turning the microphone on and off


You can temporarily switch off the handset microphone to prevent the other party from listening in while you consult with someone in your office.



You are conducting a call.

if available:

 Press the "Microphone" key. The LED lights up.

 Press the "Microphone" key. The LED goes out.


The microphone is reactivated.

Step by Step

Calling a second party (consultation)

You can call a second party while a call is in progress. The first party is placed on hold.

Prerequisite: The "Consult" key is configured on your phone.

 Press the "Consult" key. The LED flashes.



Call the second party.

Returning to the first party



Press the "Consult" key and wait two seconds.

or



Press the "Consult" twice.

Switching to the held party (alternating)



Press the "Consult" key.



Enter the code. The LED continues to flash.

Combine the calling parties into a three-party conference



Press the "Consult" key.



Enter the code. The LED goes out.

Allowing call partners to continue a conference after you exit



Replace the handset.



For more information on conferences, see
→ page 37.

Step by Step**Transferring a call**

If the person you are speaking to wants to talk to another colleague of yours, you can transfer the call that colleague.



Press the "Consult" key. The LED flashes.



Enter the number of the party to which you want to transfer the call.



Announce the call, if necessary.



Replace the handset.

Step by Step

Call forwarding

Using variable call forwarding

You can immediately forward internal or external calls to different internal or external telephones (destinations). (External destinations require special configuration in the system.)




When call forwarding is active, a special dial tone sounds when you lift the handset.

If DID DTMF is active (contact your service personnel), you can also forward calls to this destination. Destinations: fax = 870, DID = 871, fax DID = 872.

The phone is in idle mode → page 13.

Enter the code.



Enter the forwarding type you want:

1=all calls, 2=external calls only, 3=internal calls only.




Enter the destination number (external destinations with external code).

Deactivating call forwarding

The phone is in idle mode → page 13.

Enter the code.




Step by Step

Forwarding key

Your service personnel can program the "forwarding" function on a function key on your OpenStage 10 T. This forwarding action can be programmed either "completely" or "incompletely".


Activating forwarding

Prerequisite: Your service personnel programmed the forwarding key "completely".

 Press the forwarding key. The LED lights up.

The permanently programmed forwarding function is activated.

or **Prerequisite:** Your service personnel programmed the forwarding key "incompletely".

 Press the forwarding key. The LED lights up.


 or  or 

Enter the forwarding type you want:
1=all calls, 2=external calls only, 3=internal calls only.



Enter the destination number (external destinations with external code).

Deactivating call forwarding

 Press the forwarding key. The LED goes out.

Step by Step

Using call forwarding no reply (CFNR)

Calls that are not answered after three rings (=default, can be adjusted by service personnel) or that are received while another call is ongoing can be automatically forwarded to a specified telephone.

The phone is in idle mode → page 13.



Enter the code.



Enter the destination number.

- Enter the internal station number for internal destinations
- Enter the external code and the external station number for external destinations

Deactivating call forwarding no reply

The phone is in idle mode → page 13.



Enter the code.

Step by Step

Call forwarding in the carrier network and forwarding multiple subscriber numbers (MSN) (not for U.S.)

If this function has been configured (contact your service personnel), you can forward calls to your assigned multiple subscriber number (MSN) (DID number) directly within the carrier network.

For example, you can forward your phone line to your home phone after business hours.

The phone is in idle mode → page 13.

***** **6**mno **4**ghi

Enter the code.

1 or **2**abc or **3**def

Enter the forwarding type you want:
1=immediate, 2 =on no answer, 3 =on busy.



Enter the destination number (without the external code).

Deactivating call forwarding

The phone is in idle mode → page 13.

**6**mno **4**ghi

Enter the code.

1 or **2**abc or **3**def


Enter the activated call forwarding type.
1=immediate, 2 =on no answer, 3 =on busy.

Step by Step

Using callback

You can request a callback if the internal station called is busy or if nobody answers. This also applies for external calls via ISDN exchanges. This feature saves you from having to make repeated attempts to reach the user. You receive a callback

- When the other party is no longer busy,
- When the user who did not answer has conducted another call.

 When configured (contact your service personnel), all callback requests are automatically deleted over night.



Storing a callback

Prerequisite: You have reached a busy line or no one answers.

if available:

 Press the "Callback" key. The LED lights up.


or


 Press the "Consult" key. The LED flashes.
 Enter the code.

Accepting a callback

Prerequisite: A callback was saved.

 Your telephone rings.

 Lift the handset.

 You hear a ring tone.

Deleting saved callbacks (all)

if available:

 Press the "Callback" key. The LED goes out.

or

 Enter the code.

Step by Step

Enhanced phone functions

Answering calls

Accepting a specific call for your colleague

You hear another telephone ring.



Lift the handset.



Enter the code.



Enter the number of the ringing telephone.



Accepting a call in a team → page 63.

Using the speakerphone

A colleague addresses you directly over the speaker with a speaker call. You hear a tone before the announcement.

You can answer directly via the handset.



Lift the handset and answer the call.



Placing a speaker call to a colleague → page 31.

Step by Step

Answering calls from the entrance telephone and opening the door

If an entrance telephone has been programmed, you can use your telephone to speak to someone at the entrance telephone and to activate a door opener. If you have the proper authorization (consult your service personnel), you can allow visitors to activate the door opener themselves by entering a five-digit code (using a DTMF transmitter or installed keypad).

Speaking to visitors via the entrance telephone

Prerequisite: Your telephone rings.



Lift the handset within thirty seconds. You are connected to the entrance telephone immediately.

or



Lift the handset after more than thirty seconds.



Dial the entrance telephone number.

Opening the door from your telephone during a call from the entrance telephone

if available:



Press the "Door opener" key.

or



Press the "Consult" key. The LED flashes.



Enter the code.



Dial the entrance telephone number.

Opening the door with a code (at the door)



After ringing the bell, enter the five-digit code (using the keypad or a DTMF transmitter). Depending on how the door opener has been programmed, a doorbell call signal may or may not be forwarded.

Step by Step

Activating the door opener

The phone is in idle mode → page 13.




Enter the code.



Dial the entrance telephone number.



Enter the five-digit code. Default code = "00000" (contact your service personnel).



Enter the door opener type. 1=enable with ring, 2=enable w/o ring (you can also open the door without a doorbell ring).

Deactivating the door opener

The phone is in idle mode → page 13.



Enter the code.



Dial the entrance telephone number.

Accepting a call from an answering machine

You can accept a call from an answering machine if there is an answering machine connected to your system and a key programmed for it on your phone (contact your service personnel).



The LED lights up. Press the key shown.

Step by Step

Making calls

Making calls using system speed-dial numbers

Prerequisite: You know the system speed-dial numbers (consult your service personnel).

The phone is in idle mode → page 13.

if available:



Press the "Speed Dial" key. The LED flashes.

or



Enter the code.



Enter a three-digit speed-dial number.

if nec.

Suffix-dialing



If necessary, you can suffix-dial additional digits (for example, the user's extension) at the end of the saved station number.

If this feature is configured, a suffix is automatically dialed (for example, "0" for the exchange) if no entries are made within 4 or 5 seconds.

Dialing with speed-dial keys

Prerequisite: You have configured speed-dial keys → page 31.



Lift the handset.

if available:



Press the "Speed Dial" key. The LED flashes.

or



Enter the code.





Press the key shown.



Press the required speed-dial key.

Step by Step

Configure a speed-dial key

You can program the keys  to  with ten external phone numbers.

The phone is in idle mode → page 13.

Enter the code.



Press the key shown.



Press the required speed-dial key.



First enter the external code and then the external station number (wait approx. 5 seconds).



Talking to your colleague with a speaker call

You can make a loudspeaker announcement to an internal user with a system telephone without any action on their part.

Lift the handset.



Enter the code.



Enter the station number.




Step by Step

Talking to your colleague with discreet calling (not for HiPath 500)

If this function has been configured (ask your service personnel), you can join an ongoing call conducted by an internal user at a system telephone with display. You can listen in unnoticed and speak to the internal user without being overheard by the other party (discreet calling).

The phone is in idle mode → page 13.



Enter the code.



Enter your internal station number.



Your service personnel can protect your telephone against discreet calling.

Automatic connection setup (hotline)

If this function is configured (contact your service personnel), the system automatically sets up a connection to a preset internal or external destination.



Lift the handset.


Depending on the setting, the connection is either set up immediately or only after a preset period of time (= hotline after a timeout).

Assigning a station number (not for U.S.)

If this function has been configured (contact your service personnel), you can selectively assign a specific number (DID number) to your telephone before making an external call. The assigned number then appears on the called party's display.



Lift the handset.



Enter the code.



Enter the DID number you wish to use.



Dial the external number.

Step by Step**Associated dialing/dialing aid**

If this function has been configured (contact your service personnel), you can use a dialing aid to dial numbers and set up calls for your telephone.



Lift the handset.



Enter the internal number of the party for whom you want to dial.



Enter the number you wish to dial (external with external code).

Step by Step

During a call

Using call waiting (second call)

Callers can still reach you while you are engaged in another call. A signal alerts you to the waiting call.

You can ignore or accept the second call.

When you accept the waiting call, you can either end the first call or place it on hold and resume the call later on.

You can block the second call or the signal tone (→ page 35).

Prerequisite: You are engaged in a phone call and hear a tone (every six seconds).

Ending the first call and answering the waiting call:



Replace the handset. Your telephone rings.



Answer the second call. Lift the handset.

Placing the first call on hold and answering the second call:



Press the "Consult" key. The LED flashes.



Enter the code.

You are immediately connected to the second caller. The first party is placed on hold.

Ending the second call and resuming the first one



Press the "Consult" key and wait two seconds.

or

(depending on the configuration)



Press the "Consult" twice.

Step by Step

Preventing and allowing call waiting (automatic camp-on)

If this function has been configured (ask your service personnel), you can prevent or allow a second call → page 34 from being signaled by automatic camp-on during an ongoing call.

The phone is in idle mode → page 13.

4_{ghi} 9_{wxyz} 0+

Enter the code for "Call wait.term.off"

or

* 4_{ghi} 9_{wxyz} 0+

enter the code for "Call wait.term.on".

Turning the call waiting tone on and off

You can suppress the call waiting tone (every six seconds) for external calls. A one-time special dial tone then alerts you to the waiting call.

Activating the call waiting tone

The phone is in idle mode → page 13.

8_{tuv} 7_{pqrs}

Enter the code.

Deactivating the call waiting tone

The phone is in idle mode → page 13.

* 8_{tuv} 7_{pqrs}

Enter the code.

Accepting call on hold

Prerequisite: One or more calls are on hold. The phone is idle.



Lift the handset.

* 6_{mno} 3_{def}

Enter the code.



Enter the trunk number.

Step by Step

Parking a call




You can park up to ten calls, either internal, external, or both. Parked calls can be displayed on and picked up from another telephone. This feature is useful if you want to continue a call at another phone.

Prerequisite: You are conducting a call.

 Press the "Consult" key. The LED flashes.

Enter the code.

Enter the number of the park slot (0-9) and make a note of it.


You will hear a negative confirmation tone if the park slot number you enter is already in use. Enter another one.



Replace the handset.

Retrieving a parked call

Prerequisite: One or more calls have been parked. The phone is idle.

 Lift the handset.

Enter the code.

Enter the park slot number you noted earlier.

If the park slot number you enter is not in use, you cannot retrieve the call.




If a parked call is not picked up, it is returned to the telephone from where it was parked after a specific period of time (recall).

Step by Step

Conducting a conference

In a conference call, you can talk to as many as four other parties at the same time. These may be internal or external users.

 You can only add parties to or remove them from a conference if you initiated the conference.



Lift the handset.



Call the first party.



Press the "Consult" key. The LED flashes.



Call the second party.



Announce the conference.



Press the "Consult" key.



Enter the code. The LED goes out.

A tone sounds every 30 seconds to indicate that a conference is in progress.

If the second party does not answer

Press the "Consult" key and wait two seconds.

or



Press the "Consult" twice.

Adding up to five parties to a conference

Press the "Consult" key. The LED flashes.



Call the new party.



Announce the conference.



Press the "Consult" key.



Enter the code. The LED goes out.
And so on...

Leaving a conference

Replace the handset.

Step by Step



Press the "Consult" key. The LED flashes.



Enter the code. The LED goes out.

Removing the ISDN central office party from the conference



Press the "Consult" key. The LED flashes.



Enter the code.

Activating tone dialing/DTMF suffix-dialing

You can transmit dual-tone multifrequency (**DTMF**) signals to control devices such as an answering machine or automatic information system.



You have set up a connection.



Press the "Consult" key. The LED flashes.



Enter the code.



You can use the keys through , and to transmit DTMF signals.



Ending the call also deactivates DTMF suffix dialing.

Your system may be configured so that you can start DTMF suffix-dialing immediately after setting up a connection.

Step by Step

Recording calls

If configured (contact your service personnel for details), you can record an active call.

Prerequisite: You are conducting a call.

if available:



Press the "Recording" key. The LED lights up.

or



Press the "Consult" key. The LED flashes.



Enter the code.

You and the other party hear an announcement that recording has started and as long as recording is still running, you hear an acoustic signal approx. every 15 seconds.



During recording, it is not possible to add further call parties.

Stopping recording

if available:



Press the "Recording" key which lights up. The LED goes out.

or



Press the "Consult" key. The LED flashes.



Press the "Consult" key. The LED goes out.

Listening to a recording

Playback of the recording depends on the voice recording system used (see the associated user guide or → page 52).

Step by Step

Transferring a call after a speaker call announcement in a group

If this function has been configured (contact your service personnel), you can use a speaker call (announcement, → page 62) to announce a call in progress to a group of users → page 31.

After a member of the group has accepted the call request, you can transfer the waiting party.

Prerequisite: You are conducting a call.



Press the "Consult" key. The LED flashes.



Enter the code.



Enter the group's station number.



Announce the call.
You are connected to a member of the group when this party accepts the call.



Replace the handset.



If the connection between the two other parties is not established within 45 seconds, the call from the first part returns to you (recall).

Send trunk flash (not for HiPath 500)

To activate ISDN-type services and features through the network carrier's analog trunks or those of other communications platforms (such as "consultation hold"), you must send a signal to the trunks before dialing the service code or telephone number.

Prerequisite: You have set up an external connection via an analog line.



Press the "Consult" key. The LED flashes.



Enter the code.



Enter the service code and/or telephone number.

Step by Step

If you cannot reach a destination

Call waiting (camp-on)

Prerequisite: You have dialed an internal number and hear a busy signal. It is important that you reach the called party.



Wait (approx. 5 seconds) until the busy tone is followed by the ring tone.

The called party can then respond → page 34.



The called party can prevent automatic call waiting → page 35.

If this feature is configured (contact your service personnel), you will immediately hear the ring tone.

Busy override – joining a call in progress

This function is only available if it has been configured by the service technician (contact your service personnel).

Prerequisite: You have dialed an internal number and hear a busy signal. It is important that you reach the called party.



Press the "Consult" key. The LED flashes.



Enter the code.

The called party and person to whom this party is talking hear an alerting tone every two seconds.

If the called party has a system telephone with display, the following appears on the screen: "Override: (Number or name)".

You can now start talking.


Step by Step

Using night answer

When night answer mode is active, for example during a lunch break or after office hours, all external calls are immediately forwarded to a specific internal telephone (night station). The night station can be defined by service personnel (= standard night answer service) or by you (= temporary night answer service).

Activating

The phone is in idle mode → page 13.



Enter the code.



Enter the destination number within 5 seconds (= temporary night answer service).


or



Enter the code or make no entry (= standard night answer service).

Deactivating

The phone is in idle mode → page 13.



Enter the code.

Service personnel can also configure an "automatic night answer service". The automatic night answer service activates at specific times for your telephone depending on how it is programmed.

You can deactivate the automatic night answer service or replace it with a night answer service you configured (see above).

Step by Step

Displaying and assigning call charges

Dialing with call charge assignment

You can assign external calls to certain projects.

Prerequisite: Your service personnel have defined account codes for you.



Lift the handset.



Enter the code.



Enter the account code.

if nec.



Press the key shown (must be configured; consult your service personnel).



Enter the external phone number.



You can also enter the account code during an external call.

Step by Step

Privacy/security

Activating/deactivating "Do not disturb"

If you do not wish to take calls, you can activate do not disturb. Internal callers hear the busy tone, external callers are connected to another phone, which you can specify (contact your service personnel).

Activating

The phone is in idle mode → page 13.




Enter the code.

Deactivating

The phone is in idle mode → page 13.



Enter the code.

 When you lift the handset, you will hear a special tone (continuous buzzing) reminding you that "Do not disturb" is activated.

Authorized internal callers automatically override the DND feature after five seconds.

Step by Step

Caller ID suppression

You can prevent your station number or name from appearing on the displays of external parties you call. The feature remains active until you deactivate it.

Activating

The phone is in idle mode → page 13



Enter the code.

Deactivating

The phone is in idle mode → page 13.



Enter the code.



Your service personnel can activate/deactivate caller ID suppression for all phones.

Silent Monitor (not for HiPath 500)

When configured (ask responsible service personnel), you can join in an on-going call conducted by an internal user and monitor silently and unnoticed.



Lift the handset.



Enter the code.



Enter your internal station number.

Step by Step

Monitoring a room

You can use a phone to monitor a room. This function must be enabled on the monitoring phone. When you call this phone, you can immediately hear what is happening in that room.

Activating the telephone to be monitored



Lift the handset and leave it directed towards the noise source.



Enter the code.

Deactivating the telephone to be monitored



Replace the handset.

Monitoring the room



Lift the handset.



Enter the internal station number of the phone located in the room that you wish to monitor.

Step by Step

Trace call: identifying anonymous callers (not for U.S.)

You can identify malicious external callers. You can record the caller's phone number during a call or up to 30 seconds after a call. In this case, you should not hang up.



You are conducting an external call.



Press the "Consult" key. The LED flashes.



Enter the code.



If the trace is successful, the transmitted data is stored by your network operator. Contact your service personnel.

Locking the telephone to prevent unauthorized use

You can prevent unauthorized parties from using your phone during your absence.

Prerequisite: You have configured a PIN code → page 49.

Locking the phone

The phone is in idle mode → page 13.



Enter the code.



Enter code (telephone lock) → page 49.

Unlocking the phone

The phone is in idle mode → page 13.



Enter the code.



Enter code (telephone lock) → page 49.



When the phone is locked, a special dial tone sounds when the handset is lifted. Within the system, users can make calls as normal.

Your phone can also be locked or unlocked by an authorized party → page 48.


Step by Step

Locking another telephone to prevent unauthorized use

If configured (contact your service personnel), you can lock and unlock other telephones against unauthorized access.

If a phone user locks his or her phone and forgets the personal lock code, you can use this function to unlock the phone.

The phone is in idle mode → page 13.



Enter the code.



Enter the internal station number of the phone you wish to lock/unlock.



Enter the code to lock the phone.

or



Enter the code to unlock the phone.

Step by Step

Saving your PIN

Enter a personal code to use the functions

- for protecting your phone against unauthorized use → page 47
- for using another telephone like your own → page 52
- for changing a number → page 53.

You can save this code.



If you forget your code, contact your service personnel. Your code can be reset to "00000". Your phone can also be locked or unlocked by an authorized party → page 48.

The phone is in idle mode → page 13.



Enter the code.

Enter the current five-digit PIN.
If you have not yet set a PIN, use "00000" the first time.



Enter the new PIN.



Re-enter the new PIN.

Step by Step

More functions/services


Appointments function

You can configure your phone to call you to remind you about an appointment.

You must save the relevant time of the call for this. You can enter a single appointment that will take place in the next twenty-four hours or you can enter a daily recurring appointment.

Saving appointments


The phone is in idle mode → page 13.



Enter the code.




Enter a 4-digit time such as 0905 for 9.05 (= 9.05 am) or 1430 for 14.30 (= 2.30 pm).



If the selected language is "US English" (contact your service personnel), enter code 2 for "am" or 7 for "pm".

Deleting saved reminders

The phone is in idle mode → page 13.



Enter the code.

Using timed reminders

Prerequisite: You have saved a reminder → page 50.
The saved time arrives.

Your telephone rings.



Lift the handset and replace it again.



If you do not answer the timed reminder, it is repeated five times and then deleted.

Step by Step

Sending a message

You can send short text messages to individual stations or groups of stations with system telephones. Transmitted text messages are saved as callback requests on OpenStage 10 T as well as on system telephones with no display and on ISDN, pulse or tone dialing telephones.

Creating and sending a message

The phone is in idle mode → page 13.



Enter the code.



Enter the internal station number of the recipient or group.



Select a predefined text (can be changed by service personnel). Enter the code.

0 = Please callback

5 = FAX waiting

1 = Someone is waiting

6 = Dictation please

2 = Appointment

7 = Please come see me

3 = Urgent call

8 = Please make copies

4 = Do not disturb

9 = Ready to depart

Deleting sent messages

You can delete messages already sent to ensure they are not received.

Prerequisite: The recipient has not yet accepted a sent message.

The phone is in idle mode → page 13.



Enter the code.



Texts sent to groups can only be deleted by the originator.

Step by Step

Editing incoming messages

Pay attention to the notes on → page 12.

Calling the sender

Lift the handset.

if available:

Press the "Mailbox" key.



or



Enter the code.

A connection is set up to the party who sent the message.

Deleting messages

The phone is in idle mode → page 13.

Enter the code.

All incoming messages are deleted.



Using another telephone like your own for a call

Other parties can temporarily use your phone like their own for an outgoing call.

The phone is in idle mode → page 13.

Enter the code.



Enter the number of the other user.

Enter the other user's lock code.

Dial the external number.

This state is canceled as soon as the call is ended.



Step by Step

Changing a number (after exchanging/moving/relocating a phone)

When configured (consult your service personnel), you can move your number to any other phone.

Your phone to date is then assigned the old number of your new phone; the number including phone settings (e.g. programmed keys) are exchanged.

Prerequisite: Your old and new telephone are the first telephones at each connection. The telephones are in idle state.

The following procedure is carried out on the new phone.

The phone is in idle mode → page 13.



Enter the code.



Enter own station number.



Enter code (telephone lock) → page 49.
(Not necessary if you have not set a code.)



Enter the code.



You can however connect your phone to a different port and then carry out the procedure.

Fax details and message on answering machine

If there is a fax machine or answering machine connected to your system and the "Fax service" key is programmed on your phone, this key lights up when a fax or message is received.

Deactivating signaling



Press the flashing key "Fax service". The LED goes out.

Step by Step

Resetting services and functions (system-wide cancellation for a telephone)

A general reset procedure is available for initiated functions. The following functions are deleted, if enabled:

- Forwarding on
- Advisory msg. on
- Ringing group on
- Hunt group off
- Suppress call ID
- Call waiting tone off
- Do not disturb on
- Ringer cutoff on
- Received messages:
- View callbacks

The phone is in idle mode → page 13.



Enter the code.

Step by Step

Activating functions for another telephone

If configured (contact your service personnel), you can activate and deactivate the following functions for other phones (associated service):

- Do not disturb,
code: *97/#97 → page 44
- Call forwarding,
code: *11, *12, *13, #1 → page 22
- Lock and unlock phone,
code: *66/#66 → page 47
- Ringing group,
code: *81/#81 → page 63
- Group call,
code: *85/#85 → page 62
- Reset services and functions,
code: #0 → page 54
- Control relays,
code *90/#90 → page 60
- Night answer,
code: *44/#44 → page 42
- Timed reminders,
code: *46/#46 → page 50

The phone is in idle mode → page 13.



Enter the code.



Enter the internal station number of the phone where you wish to activate the function.



Enter a code – such as *97 for Do not disturb on – and a procedure if necessary.

Step by Step

Using system functions from outside DISA (direct inward system access)

If configured (contact your service personnel), you can use an external phone like an internal station to set up an outgoing external connection via the system. You can also activate or deactivate the following system functions:

- Reset services and functions, code #0 → page 54
- Call forwarding, code *11, *12, *13, #1 → page 22
- Lock and unlock phone, code *66/#66 → page 47
- Save your PIN, code *93 → page 49
- Send a message, code *68/#68 → page 51
- Ringing group, code *81/#81 → page 63
- Group call, code *85/#85 → page 62
- Caller ID suppression, code *86/#86 → page 45
- Open door, code *61 → page 28
- Release door opener, code *89/#89 → page 29
- Control relays, code *90/#90 → page 60
- Do not disturb, code *97/#97 → page 44
- Dial using speed dial, code *7 → page 30
- Associated service, code *83 → page 55

Prerequisite: Your phone supports tone dialing (DTMF) or you can switch your phone to tone dialing. The phone is not connected to the system.



Establish a connection to the system. Enter the station number (contact your service personnel).



Wait for the continuous tone (if necessary, switch phone to tone dialing) and enter the internal number assigned to you and the corresponding PIN.



Enter the code (only required if programmed in the system).

Step by Step



Wait for the dial tone and enter the code for example, *97 for Do not disturb on. If necessary, make further entries; refer also to the user guide for dial pulse/DTMF phones.

or



Dial the external number.



You can only perform one function/establish one outgoing connection at a time.

The connection is cleared as soon as the function is successfully activated.

In the case of an external-external call, the connection is cleared as soon as one of the call partners hangs up.


Step by Step

Controlling Connected Computers or Their Programs/Tel. Data Service

If this function has been configured (contact your service personnel), you can control connected computers or programs running on them, such as hotel services or information systems, from your telephone.

Prerequisite: You have set up a connection.

Press the "Consult" key. The LED flashes.



Enter the code.

Press the key shown. The lamp is flashing. Enter the code.

For entering data, you are guided by the connected computer. However, depending on configuration (contact your service personnel), you must activate your entries in one of the following ways:

Inputs in en-bloc mode



Enter data.



Complete your entry.

or Inputs in online mode

The connected computer processes your entries directly.



Enter the code.



Enter data.

Step by Step

Communicating with PC applications over a CSTA interface

If configured (contact your service personnel), you can use your phone to communicate with PC applications (CSTA = **C**omputer **S**upported **T**elecommunications **A**pplications). Information is sent to the application and received from the application via acoustic signaling.

if available:

Press the "Data I/O" key.

or



Enter the code.



Enter the three-digit ID for the application you wish to control.



Use the relevant keys to communicate with the application.

Temporarily interrupting communication with the application



The phone is ringing. You answer the call.



The "Data I/O" key flashes: Communication to the application is automatically interrupted.

Resuming communication with the application



Press the flashing "Data I/O" key. The LED lights up.

Ending communication with the application



Lift the handset and replace it again.

Step by Step

Controlling relays (only for HiPath 3000)

If this function has been configured (contact your service personnel), you can use up to four relays to enable/disable different devices (such as a door opener). Depending on how you program the relays, you can activate and deactivate them manually them or configure them to activate and deactivate automatically (after timeout).

Activating

The phone is in idle mode → page 13.

* 9 wxyz 0 +

Enter the code.

1 ... 4 ghi

Enter the relay.

Deactivating

The phone is in idle mode → page 13.

9 wxyz 0 +

Enter the code.

1 ... 4 ghi

Enter the relay.

Step by Step

Paging persons (not for U.S., not for HiPath 500)

If radio paging equipment (PSE) is connected to your system (contact your service personnel), you can locate people via their pocket receivers.

Pocket receivers signal a call request to the person you want to page. This person can then answer the page at the nearest phone.

Paging persons

To ensure that you can be found, you must have enabled a ringing group → page 63, call forwarding → page 22 or call forwarding-no answer to the internal station number of your PSE.

A call request is signaled automatically.

Answering the page from the nearest telephone



Lift the handset.



Enter the code.



Enter own station number.

Step by Step

Using team functions

If configured (consult your service personnel), your telephone is part of a team. The team consists of internal phones that are able to use certain functions.

Activating/deactivating a group call

If configured (consult your service personnel), you belong to one or more groups of stations, which can be reached via hunt group or group call station numbers. Incoming calls are signaled one after the other (= hunt group) or simultaneously (= group call) on all phones in the group, until a group member answers the call.

Each station in the group can still be reached via their personal station number.

You can activate and deactivate the audible signal for a hunt group or group call.

If the LED for a programmed "Hunt group" key is lit, the audible tone was activated for at least one group.

Activating

The phone is in idle mode → page 13.

if available:



Press the "Hunt group". The LED lights up.

or



Enter the code.

Deactivating

The phone is in idle mode → page 13.

if available:



Press the "Hunt group". The LED goes out.

or



Enter the code.



If you have deactivated the audible tone for the group you belong to, you will hear a special dial tone when you lift the handset.

Step by Step

Accepting a call for another member of your team

You can use your own telephone to accept calls for other telephones in your team, even while engaged in an ongoing call. To do this, contact your service personnel to find out if a pickup group has been configured.

Prerequisite: Your telephone rings briefly.

Lift the handset.



Enter the code.

Ringling group

You can have calls for your telephone signaled audibly at up to five other internal phones. The phone that answers the call first receives the call.

Saving phones for the ringing group

The phone is in idle mode → page 13.



Enter the code.



Enter your internal station number.

Removing all telephones in a call ringing group

The phone is in idle mode → page 13.



Enter the code.

Step by Step

Uniform Call Distribution (UCD)

If configured (consult your service personnel), you may belong to a group of stations (agents), to which calls are distributed.

An incoming call is always assigned to the agent idle the longest.

Logging on/off for a service

The phone is in idle mode → page 13.



Enter the code for "Log on".



Enter your identification number ("Agent: <x>"; contact your service personnel).

or



Enter the code for "Log off".

Logging on and off during your shift

The phone is in idle mode → page 13.



Enter the code for "Not available".


or



Enter the code for "Available".

Activating/deactivating work time

You can request/activate work time to ensure you have enough time to wrap up the last call. Your phone is excluded from call distribution for a set period or until you log back on.



You have or had a connection.



Enter the code for "Work on".

or

The phone is in idle mode → page 13.



Enter the code for "Work off".

Step by Step



Turning the night service on and off for UCD

The phone is in idle mode → page 13.

Enter the code for "UCD night on".
depending on the configuration:



Press the key shown.



Enter the station number.

or



Enter the code for "UCD night off".


Step by Step

Individual phone configuration

Adjusting audio settings


Adjusting the receiving volume during a call

You are conducting a call.



Raise or lower the volume. Keep pressing the keys until the desired tone is set.


Adjusting the ring volume



Press one of the keys shown in idle mode.




Press the key shown.



Raise or lower the volume. Keep pressing the key until the desired volume is set.


Adjusting the ring tone



Press one of the keys shown in idle mode.



Press the key shown.



To adjust the ring tone: Keep pressing the keys until the desired tone is set.

Step by Step

Testing the phone

Phone functions, testing

You can test your phone's functionality.

The phone is in idle mode → page 13.



Enter the code.

If everything is functioning correctly:

- all LEDs on the phone light up and
- the ring tone is audible.

Fixing problems

Contact partner in the case of problems

Contact your service personnel if a fault persists for more than five minutes, for example.

Troubleshooting

Pressed key does not respond

Check if the key is stuck.

Telephone does not ring

Check whether the "Do not disturb" function is activated on your telephone. When you lift the handset, you will hear a special tone. If so, deactivate it → page 44.

You cannot dial an external number

Check whether your telephone is locked. When you lift the handset, you will hear a special tone. If so, unlock your phone → page 47.

To correct any other problems

First contact the relevant service personnel. If the service personnel are unable to correct the problem, they must contact Customer Service.

Caring for your telephone

- Never allow the telephone to come into contact with coloring, oily or aggressive agents.
- Always use a damp or antistatic cloth to clean the telephone. Never use a dry cloth.
- If the telephone is very dirty, clean it with a diluted neutral cleaner containing surfactants, such as a dish detergent. Afterwards remove all traces of the cleaner with a damp cloth (using water only).
- Never use aggressive or alcohol-based cleansers on plastic parts. The use of scouring agents is also forbidden.

Index

A

Agents	64
Announcement	31
Answering machine	53
call pickup	29
Assigning a DID number	32
Associated dialing/dialing aid	33
Associated service	55
Audio keys	11
Automatic camp-on	
preventing and allowing	35
Automatic connection setup	32
Automatic line seizure	17

B

Busy override	41, 45
---------------------	--------

C

Call	
accepting	15
accepting from the answering machine	29
accepting, group	63
answering	15
distributing	64
entrance phone	28
forwarding	22
parking	36
pickup, directed	27
rejecting	19, 28
retrieving from park	35, 36
transferring	21
Call charge assignment	43
Call forwarding	22
MSN in CO	25
Call volume	15, 66
Call waiting	41
accepting	34
allowing	35
preventing	35
Call waiting (camp-on)	
tone off	35

Call waiting on/off	35
Call waiting tone on/off	35
Callback	26
Caller ID suppression	45
Calling a second party	20
Calls	
recording	39
Calls in queue	64
Caring for your telephone	68
CE marking	2
Central telephone lock	48
Change number	53
Changed phone	53
Cleaning your phone	68
Conference	20
Connection setup	
automatic	32
Connection setup, automatic	32
Consultation	20
Control relays	60

D

Details, fax	53
Dialing	
internal/external calls	17
on-hook dialing	17
with DDS keys	18
with speed dialing	30
with the dialing aid	33
Dialing internal calls	17
Dialing numbers	
dialing the last number	18
using redial	18
Direct inward system access (DISA)	56
DISA	56
Discreet calling	32
Distributing calls	64
Do not disturb	44
Door release	29

E

Entrance telephone	28
External code	17

F

Fax details	53
Forwarding	
MSN in CO	25
multiple subscriber number (MSN)	25
Forwarding key	23
Forwarding MSN in CO	25
Function keys	11
Functions	
activating/deactivating for another tele- phone	55
resetting	54
using from the outside	56
Functions, activating	13

G

General information	8
Group call	62

H

Handsfree answerback	27
Hotline	32
Hotline delayed	32
Hunt group	62

I

Important information	3
Information	2

L

LED display	
direct station selection keys	12
function keys	12
Line seizure, automatic	17
Location of the telephone	3
Locking all phones	48
Locking/unlocking	47

M

Mailbox	52
Making external calls	17
Making mobile calls	52
Making trunk calls	17
Malfuctions	68
Message	
answering	52
deleting/displaying	51
receiving	52
sending	51
Move function	53
Move with phone	53
Multiple subscriber number (MSN)	
forwarding	25

N

Night answer	42
--------------------	----

O

Open listening	16
Opening a door	
with a code	28
Operating principle	13
Operational elements	10

P

Parking a call	36
Personal identification number	49
Phone	
caring for	68
cleaning	68
locking another	48
locking/unlocking centrally	48
operating	13
testing	67
using another like your own	52
Phone functions, testing	67
Phone settings	66
Pickup (call)	27, 63

- PIN 49
 for a telephone 47
 PIN, saving 49
 Programming your telephone 66
 Project calls 43
 Project code, account code 43
- R**
- Radio paging equipment (PSE) 61
 Recall 40
 Receiving volume 15, 66
 Recording 39
 Redialing a number 18
 Relays 60
 Relocate 53
 Resetting functions 54
 Resetting services 54
 Ring tone 66
 Ring volume 66
 Ringing group 63
 Room monitor 46
- S**
- Second call
 accepting 34
 Second layer 18
 Secret busy override 45
 Setting your telephone 66
 Settings 66
 Shift 18
 Shift key 18
 Silent monitor
 no tone 45
 Speaker call 31
 Special dial tone 12, 44
 Speed-dialing
 dialing 30
 saving station speed-dialing 31
 suffix-dialing 30
 system 30
- Station number
 assigning 32
 deactivating display 45
 suppressing 45
 Station speed-dialing 31
 Suffix-dialing
 automatic 30
 DTMF tone dialing 38
 System speed-dialing 30
 System-wide cancellation 54
- T**
- Tel. data service 58
 Telephone
 locking 47
 locking/unlocking 47
 settings 66
 Telephone test 67
 Temporary phone 52
 Testing the telephone 67
 Text
 answering 52
 receiving 52
 Text message
 deleting/displaying 51
 sending 51
 Three-party conference 20
 Timed reminder 50
 Timed reminder, answering 50
 Toggle/Connect 20
 Tone dialing 38
 Tone dialing (DTMF dialing) 38
 Trace call 47
 Transfer (call) 21
 Troubleshooting 68
 Trunk flash 40
- U**
- UCD 64
 User support 8

V

Variable call forwarding 22

Volume

 keys 11

W

Work time 64

Overview of functions and codes

The following table lists all available functions. If configured (contact your service person-
nel), you can activate functions by entering a code or pressing a function key.











































































Functions		Operating steps
Accept call	directed	* 5kl 9wxyz internal
	group	* 5kl 7pqrs
Accept call on hold		* 6mno 3def trunk no.
Adjust ring tone		(or) 2abc or
Answer call		
Answer page (not for U.S., not for HiPath 500)		* 5kl 9wxyz internal
Assign station number (not for U.S.)		* 4ghi 1 MSN external
Associated dialing		* 6mno 7pqrs internal stn no.
Associated service		* 8tuv 3def internal code
Busy override		Stn busy "Consult" * 6mno 2abc
Call charge assignment/account code		* 6mno 0+ project code (if nec.) external
Call forwarding on		* 1 1 stn no.
		* 1 2abc stn no.
		* 1 3def stn no.
off	# 1	
CFNR on		* 4ghi 9wxyz 5jkl stn no.
CFNR off		# 4ghi 9wxyz 5jkl
in the carrier network on		* 6mno 4ghi 1 external
		* 6mno 4ghi 2abc external
		* 6mno 4ghi 3def external
in the carrier network off		# 6mno 4ghi 1
		# 6mno 4ghi 2abc
		# 6mno 4ghi 3def

Functions	Operating steps
Call park <hr/> unpark	"Consult" * 5 jkl 6 mno (0+ ... 9 wxyz) <hr/> # 5 jkl 6 mno (0+ ... 9 wxyz)
Call waiting	internal stn busy, wait 5 s
Callback <hr/> delete <hr/> answer (call)	"Callback" <hr/> # 5 jkl 8 tuv <hr/>
Change call volume	+ or -
Change number	* 9 wxyz 4 ghi 1 9 wxyz own stn no. code # 9 wxyz 4 ghi 1 9 wxyz
Conference <hr/> start <hr/> party does not answer, proceed with 1st call <hr/> add party (max. five) <hr/> leave conference <hr/> end conference <hr/> remove ISDN central office party from conference	stn no. "Consult" stn no. "Consult" * 3 def <hr/> (1x or 2x) "Consult" <hr/> "Consult" * 3 def etc. <hr/> <hr/> "Consult" # 3 def <hr/> "Consult" * 4 ghi 9 wxyz 1
Consultation <hr/> end, resume 1st call <hr/> Toggle/Connect <hr/> start three-party conference <hr/> connect caller	"Consult" stn no. <hr/> (1x or 2x) "Consult" <hr/> "Consult" * 2 abc <hr/> "Consult" * 3 def <hr/>
Control Relay (only for HiPath 3000) <hr/> on <hr/> off	* 9 wxyz 0+ 1 ... 4 ghi <hr/> # 9 wxyz 0+ 1 ... 4 ghi

Functions	Operating steps
Data I/O Service	4 _{ghi} code
Direct Answer	
Discreet calling (not for HiPath 500)	internal
Do not disturb	on
	off
Door opener	entrance phone call or after 30 s internal
	open door "Consult" internal
	enable with ring int. + code
	enable w/o ring int. + code
	lock internal
DTMF suffix dialing/tone dialing	"Consult"
End call	or "Release"
Group call	leave or or group
	rejoin or or group
Hotline	
Make calls	stn no.
Message	send internal (+ ...)
	delete (sent)
	call sender or "Mailbox"
	delete (received)

Overview of functions and codes

Functions		Operating steps
Microphone	deactivate	"Microphone"
	activate	"Microphone"
Night answer	temporary - on	internal
	standard - on	
	off	
Phone	lock	code
	unlock	code
	central lock	internal
	central unlock	internal
Phone test		
Record call	"Consult"	
Redial	"Redial"	
Reject calls	"Release"	
Reset services		
Ringing group	on	internal
	off	
Room Monitor	on	
	off	
	monitor	internal
Save PIN	old code 2x new code	

Functions		Operating steps
Second call	end 1st call, accept 2nd call	
	Call waiting	 "Consult" *  
	end, resume first call	(1x or 2x)  "Consult"
	prevent automatic camp-on	    
	allow automatic camp-on	*    
	camp-on tone on	   
	camp-on tone off	*   
Silent monitor (not for HiPath 500)		 *     internal
Speaker call		 *    internal 
Speed dial	system, dial	  „Speed Dial"  (000...999) or  *   (000...999)
	station, dial	  "Speed Dial"  (*0...*9) or  *   (*0...*9)
	station, save	*   * 0...9   external 
	Suppress call ID	on  *    off  #   
Tel. data service		  "Consult" *   
Timed reminder	save	*    (time e.g.: 0905) 
	delete reminder	#   
	Answer timed reminder	 
Trace call (not for U.S.)		  "Consult" *  

Overview of functions and codes

Functions	Operating steps
Transfer call after a speaker call announcement in a group	
Trunk flash (not for HiPath 500)	
UCD Log on at the beginning of a shift Log off at the beginning of a shift Log off work Log on work Work time on Work time off Night answer on Night answer off	
Use mailbox	 or
Use phone like your own	

Communication for the open minded

Siemens Enterprise Communications
www.siemens-enterprise.com

Copyright © Siemens Enterprise
Communications GmbH & Co. KG
Hofmannstr. 51
80200 München
Deutschland

Siemens Enterprise
Communications GmbH & Co. KG
is a Trademark Licensee of Siemens AG

Reference No:
A31003-S2000-U121-4-7619

The information provided in this document contains merely general descriptions or characteristics of performance which in case of actual use do not always apply as described or which may change as a result of further development of the products.

An obligation to provide the respective characteristics shall only exist if expressly agreed in the terms of contract. Availability and technical specifications are subject to change without notice. OpenScape, OpenStage and HiPath are registered trademarks of Siemens Enterprise Communications GmbH & Co. KG. All other company, brand, product and service names are trademarks or registered trademarks of their respective holders.